

List of Peristaltic Pumps

No.	Series Name	Model Number	Motor Type	Discharge Pressure Initial Value (Mpa)	Standard Flow Rate (ml/min.)	Tube Size (ID mm x OD mm)	Tube Material	Rated Voltage	Power Consumption(Motor) At Rated Voltage (W)	Outor Dimensions (mm)
1	RP-K	RP-K03F-30A-DC24V	DC Gear Motor	0.1	30	3.2 x 6.4	Pharmed	DC24V	3.4	77x96x95.5
2	RP-K	RP-K03R-30A-DC24V	DC Gear Motor	0.1	30	3.2 x 6.4	Fluran	DC24V	3.4	77x96x95.5
3	RP-K	RP-K03S-30A-DC24V	DC Gear Motor	0.1	30	3 x 5	Silicone	DC24V	3.4	77x96x95.5
4	RP-K	RP-K05F-90A-DC24V	DC Gear Motor	0.1	95	4.8 x 7.9	Pharmed	DC24V	6.0	77x96x98.5
5	RP-K	RP-K05R-90A-DC24V	DC Gear Motor	0.1	95	4.8 x 7.9	Fluran	DC24V	6.0	77x96x98.5
6	RP-K	RP-K05S-90A-DC24V	DC Gear Motor	0.1	95	4.8 x 7.9	Silicone	DC24V	6.0	77x96x98.5
7	RP-K	RP-K05F-200A-DC24V	DC Gear Motor	0.1	200	4.8 x 7.9	Pharmed	DC24V	5.5	77x96x95.5
8	RP-K	RP-K05R-200A-DC24V	DC Gear Motor	0.1	200	4.8 x 7.9	Fluran	DC24V	5.5	77x96x95.5
9	RP-K	RP-K05S-200A-DC24V	DC Gear Motor	0.1	200	4.8 x 7.9	Silicone	DC24V	5.5	77x96x95.5
10	RP-M (DC)	RP-M02F-5A-DC24V	DC Gear Motor	0.05	6	2 x 4	Pharmed	DC24V	3.6	74x74.5x98
11	RP-M (DC)	RP-M02S-5A-DC24V	DC Gear Motor	0.05	6	2 x 4	Silicone	DC24V	3.6	74x74.5x98
12	RP-M (DC)	RP-M03F-15A-DC24V	DC Gear Motor	0.05	15	3 x 5	Pharmed	DC24V	3.6	74x74.5x98
13	RP-M (DC)	RP-M03S-15A-DC24V	DC Gear Motor	0.05	15	3 x 5	Silicone	DC24V	3.6	74x74.5x98
14	RP-M (DC)	RP-M04S-40A-DC24V	DC Gear Motor	0.05	43	4 x 6	Silicone	DC24V	5.8	74x74.5x101
15	RP-M (DC)	RP-M04N-40A-DC24V	DC Gear Motor	0.05	43	3.9 x 5.8	Norprene	DC24V	5.8	74x74.5x101
16	RP-M (DC)	RP-M04S-120A-DC24V	DC Gear Motor	0.05	120	4 x 6	Silicone	DC24V	6.9	74x74.5x89
17	RP-M (DC)	RP-M04N-120A-DC24V	DC Gear Motor	0.05	120	3.9 x 5.8	Norprene	DC24V	6.0	74x74.5x89
18	RP-M (AC)	RP-M02F-5A-AC100V	AC Synchronous Motor	0.05	6	2 x 4	Pharmed	AC100V	5.0	74x74.5x48
19	RP-M (AC)	RP-M02S-5A-AC100V	AC Synchronous Motor	0.05	6	2 x 4	Silicone	AC100V	5.0	74x74.5x48
20	RP-M (AC)	RP-M04S-20A-AC100V	AC Synchronous Motor	0.05	20	4 x 6	Silicone	AC100V	5.0	74x74.5x48
21	RP-M (AC)	RP-M04N-20A-AC100V	AC Synchronous Motor	0.05	20	3.9 x 5.8	Norprene	AC100V	5.0	74x74.5x48
22	RP-M (AC)	RP-M04S-35A-AC100V	AC Synchronous Motor	0.05	34	4 x 6	Silicone	AC100V	5.0	74x74.5x48
23	RP-M (AC)	RP-M04N-35A-AC100V	AC Synchronous Motor	0.05	34	3.9 x 5.8	Norprene	AC100V	5.0	74x74.5x48
24	RP-S	RP-S06R-500A-DC24V	DC Gear Motor	0.05	500	6.4 x 9.5	Fluran	DC24V	9.0	81x126x81
25	RP-S	RP-S06S-500A-DC24V	DC Gear Motor	0.05	500	6.4 x 9.5	Silicone	DC24V	9.0	81x126x81
26	RP-S	RP-S06N-500A-DC24V	DC Gear Motor	0.05	500	6.4 x 9.5	Norprene	DC24V	9.0	81x126x81
27	RP-2S	RP-2S06R-500A-DC24V	DC Gear Motor	0.1	500x2	6.4 x 9.5	Fluran	DC24V	48.0	81x126x120
28	RP-2S	RP-2S06S-500A-DC24V	DC Gear Motor	0.1	500x2	6.4 x 9.5	Silicone	DC24V	48.0	81x126x120
29	RP-2S	RP-2S06N-500A-DC24V	DC Gear Motor	0.1	500x2	6.4 x 9.5	Norprene	DC24V	48.0	81x126x120
30	RP-Q	RP-Q1-S-P45A-DC3V	DC Gear Motor	0.05	0.45	1.5 x 2.5	Silicone	DC3V	0.12	12x14x31.5
31	RP-Q	RP-Q1.2N-P20A-DC3V	DC Gear Motor	0.05	0.20	1.2 x 2.5	Norprene	DC3V	0.12	12x14x31.5
32	RP-G	RP-G04S-P70A-DC24V	DC Geat Motor	0.05	70	4 x 6	Silicone	DC24V	2.50	96x68x35
33	RP-G	RP-G04N-P70A-DC24V	DC Geat Motor	0.05	70	4 x 6	Norprene	DC24V	2.50	96x68x35
34	RP-G II	RP-G II 03W-50A-DC24V	DC Geat Motor	0.05	50	3 x 5	TM-15	DC24V	2.50	74x47.5x26
35	RP-G II	RP-G II 03W-50A-DC12V	DC Geat Motor	0.05	50	3 x 5	TM-15	DC12V	2.50	74x47.5x26
36	RP-G II	RP-G II 02W-10A-DC12V	DC Geat Motor	0.05	12	2 x 4	TM-15	DC12V	2.50	74x47.5x26
37	RP-G II	RP-G II 02W-10A-DC6V	DC Geat Motor	0.05	12	2 x 4	TM-15	DC6V	2.50	74x47.5x26
38	RP-C	RP-C2.5S-5A-DC12V	DC Gear Motor	0.05	2	2.5 x 4.0	Silicone	DC12V	N/A	73.0 x 46.0 x 40.1
39	RP-C	RP-C2.5S-5A-DC24V	DC Gear Motor	0.05	5	2.5 x 4.0	Silicone	DC24V	N/A	73.0 x 46.0 x 40.1
40	RP-C	RP-C2.5S-7A-DC12V	DC Gear Motor	0.05	7	2.5 x 4.0	Silicone	DC12V	N/A	73.0 x 46.0 x 40.1
41	RP-C	RP-C2.5S-10A-DC12V	DC Gear Motor	0.05	10	2.5 x 4.0	Silicone	DC12V	N/A	73.0 x 46.0 x 40.1
42	RP-C	RP-C2.8N-2A-DC12V	DC Gear Motor	0.05	1.8	2.8 x 4.5	Norprene	DC12V	N/A	73.0 x 46.0 x 40.1
43	RP-C	RP-C2.8N-5A-DC24V	DC Gear Motor	0.05	4.5	2.8 x 4.5	Norprene	DC24V	N/A	73.0 x 46.0 x 40.1
44	RP-C	RP-C2.8N-7A-DC12V	DC Gear Motor	0.05	6.5	2.8 x 4.5	Norprene	DC12V	N/A	73.0 x 46.0 x 40.1
45	RP-C	RP-C2.8N-9A-DC12V	DC Gear Motor	0.05	9	2.8 x 4.5	Norprene	DC12V	N/A	73.0 x 46.0 x 40.1
46	RP-C III	RP-C III 1.6S-2A-DC3V	DC Gear Motor	0.03	2	1.6 x 3.2	Silicone	DC3V	N/A	44.5 x 33.4 x 26.0
47	RP-C III	RP-C III 1.6S-3A-DC5V	DC Gear Motor	0.03	3	1.6 x 3.2	Silicone	DC5V	N/A	44.5 x 33.4 x 26.0
48	RP-C III	RP-C III 1.6N-2A-DC3V	DC Gear Motor	0.03	2	1.6 x 3.2	Norprene	DC3V	N/A	44.5 x 33.4 x 26.0
49	RP-C III	RP-C III 1.6N-3A-DC5V	DC Gear Motor	0.03	3	1.6 x 3.2	Norprene	DC5V	N/A	44.5 x 33.4 x 26.0
50	RP-C III	RP-C III 1.6R-2A-DC3V	DC Gear Motor	0.03	2	1/16" x 1/8"	Fluran	DC3V	N/A	44.5 x 33.4 x 26.0
51	RP-TX	RP-TX	DC Gear Motor	0.03	0.1-40 μ	0.5 x 1.5	Silicone	DC3V	N/A	33 x 21.5 x 12
52	RP-TX	RP-TX	DC Gear Motor	0.03	0.1-40 μ	0.5 x 1.5	Norprene	DC3V	N/A	33 x 21.5 x 13

*Discharge Pressure is typical.
 **Power consumption is not applicable
 RP-C series are customized for customers.
 These models are typical ones.